



# Knowledge Base

powered by  ALARM.COM

---

## Slim Line II Wi-Fi Doorbell Camera (ADC-VDB105x/106x) - Data Sheet

### Overview

The Slim Line II Wi-Fi Doorbell Camera makes it easy to deliver front door awareness to even more customers!

The Slim Line II delivers an engaging customer experience with Two-Way Audio, live and recorded video, and notifications. The Slim Line II has an integrated camera, PIR motion sensor, and digital microphone and speaker, that enables homeowners to answer the door and speak right from their app. Customers can also record doorbell-triggered clips, set motion-triggered automation rules, and receive real-time alerts.



[https://answers.alarm.com/Partner/Installation\\_and\\_Troubleshooting/Video\\_Devices/SkyBell\\_Doorbell\\_Cameras/Slim\\_Line\\_II...](https://answers.alarm.com/Partner/Installation_and_Troubleshooting/Video_Devices/SkyBell_Doorbell_Cameras/Slim_Line_II...)

Updated: Fri, 20 Jan 2023 15:26:15 GMT



## Features

- 720p live video



[https://answers.alarm.com/Partner/Installation\\_and\\_Troubleshooting/Video\\_Devices/SkyBell\\_Doorbell\\_Cameras/Slim\\_Line\\_II...](https://answers.alarm.com/Partner/Installation_and_Troubleshooting/Video_Devices/SkyBell_Doorbell_Cameras/Slim_Line_II...)

Updated: Fri, 20 Jan 2023 15:26:15 GMT

- Doorbell with integrated camera
- PIR-triggered motion sensitivity (low, medium, and high settings)
- Digital microphone and speaker
- Doorbell-triggered clips
- Motion-triggered automation rules
- Real-time alerts
- Battery heater for improved cold weather performance

## Included accessories

- Wall mounting bracket
- Wall screws
- Masonry anchors

## Specifications

### AC Power

A SkyBell Doorbell Camera wired to an in-home mechanical or digital doorbell chime requires 16–24 VAC, 10 VA (20 VA if two doorbell cameras are on the circuit).

Transformers without a doorbell chime need a 10 Watt, 10 Ohm resistor.

**Note:** Digital chimes require a digital doorbell adapter to be compatible. For more information, see [Digital doorbell adapter -installation guide](#).

### DC Power

A SkyBell Doorbell Camera requires a DC power supply rated at exactly 12 VDC, 0.5–1 Amps.

### Wi-Fi

Compatible with Wi-Fi 802.11 b/g/n/ ac, 2.4 and 5 GHz

### Minimum Bandwidth Requirement

2 Mbps

### Video Camera

1.3 MP, full-color

### Lens/angle of view

170° horizontal, 110° vertical

### Resolution

Live: 720p (adjustable to lower resolution if required)  
Recorded: 720p

### Night vision

Infrared



**Microphone**

Omni-directional

**Motion Sensor**

Detects motion up to 8 ft range

**Dimensions (width x depth x weight)**

1.4 x 4.8 x 1.1" (3.65 x 12.2 x 2.86 cm); 3.1 oz (87.9 g)

**Weather Rating**

IPX4 rated

**Operating Temperature**

-40°F to 122°F (-40°C to 50°C)

**Operating Humidity**

Operating Humidity (RH): 10% to 80%

