

# MCW-S/A

Desk Mount Stand

Use with:

**AX, GT, JF, JK, JO, JP, and KB Systems**

## - INSTRUCTIONS -

The MCW-S/A is a stand that will allow you to locate an Aiphone monitor station on a desk or tabletop. This stand has two angle settings, enabling the user to select the optimal mounting angle for the monitor station (45° or 60°).

### MOUNTING:



MCW-S/A



JF-2MED on MCW-S/A  
(shown at 60°)

45° Angle



Dimensions:  
Faceplate: 4½" W x 6½" H  
Base: 4½" W x 7⅞" D  
Height at 45°: 5⅝"  
Height at 60°: 6"

60° Angle



Recommended mounting hole position by system:  
**Top :**  
AX  
KB  
**Bottom:**  
GT  
JF  
JK  
JO  
JP

### MOUNTING:

1. Attach the intercom's mounting bracket to the MCW-S/A utilizing the appropriate set of mounting holes. *(Nuts and washers are supplied with the MCW-S/A; screws are supplied with the intercom, except for JO.)*
2. Set the angle of the MCW-S/A by adjusting the rear support arm for either a 45° or 60° angle.
3. Lock the rear support arm into position to prevent the MCW-S/A from collapsing.
4. Feed the wires through the back of the MCW-S/A and attach to the intercom unit.
5. Mount the station onto the mounting bracket.



AX-8MV on MCW-S/A  
(shown at 45°)



GT-1C on MCW-S/A  
(shown at 60°)



KB-3MRD on MCW-S/A  
(shown at 60°)