

Specifications

Power draw:

- Connectors:
- Battery connection
- 8 zone inputs
- AC input (16 VAC)
- Aux/Bell
- KBus 4-wire

• 2 PGM outputs (3A)

Dimensions: 190 x 95 mm (7.5 x 3.75 in)

Included in the box

- UNO IP hybrid alarm panel
- Battery connector cable
- Zone and battery resistors
- Stand-offs



Full IP security panel with on-board wireless option.

- Up to 8 partitions
- Up to 128 zones
- Up to 128 users
- 2 on-board high power PGM outputs. (more available)
- Mounts in a standard security enclosure
- Supports full UL/ULC alarm monitoring over IP
- LTE option available
- Supports all Connect2Go service and app features
- Alexa and Google Home compatible

Total Control

- Connect2Go App available on Google Play or iTunes store.
- Full remote control of all panel features from App on all partitions.
- Full event logging.
- Event alerts by push notifications, email or SMS text.

Remote Programming

- Built in support for remote programming from your Connect2Go dealer portal.
- Firmware and features remotely upgradeable.

Extended Compatibility

- Alexa and Google Home support.
- Compatible with many DSC keypads and peripherals. Honeywell coming soon.

works with Google Home



UNO8

- 8-zone expander board
- 2 high-power 3A programmable outputs (no need for external relays)



Accessories

UNO-RF433

- RF zone expander module
- Add Connect2Go 433
- wireless sensors

Sidekick LTE

LTE backup or primary communications for UNO panels.